

How to add/replace a new camera to NVR?

In case the camera loses connection with NVR accidentally or you want to add a new camera to NVR system, please pair/match code the camera with NVR as below steps:

- 1 Take the camera near NVR.
- 2 Plug camera to power outlet via the provided 12V 1A plug.
- 3 Use Ethernet cable (RJ45) to connect camera with NVR, the WAN indicator light at back panel of NVR will turn on.



- 4 Right click mouse to enter menu "Video Manage", the upper box shows information of camera, and lower box shows channel information of NVR.
- 5 If the channel status at lower box shows "IPC Disconnect", "Connect Fail", "Different Segment" ..., selects that channel with mouse, then click "Delete" and the status of that channel will be "No video source".
- 6 Click "Search" in the upper box, new IP address will pop up in minute and then click "Match Code".
- 7 The camera will be connecting with NVR and "Wi-Fi add" interface will pop up.
- 8 Click "Exit" until the camera's IP address pops up for that channel (The IP address will be 172.20.14.xx for wireless mode).
- 9 The picture of camera will be shown on monitor and the status of that channel will be "Connect Success" on video manage interface.
- 10 Then you can disconnect the Ethernet cable and install the camera at anywhere you want (Camera should be within the NVR Wi-Fi range).

Video Manage

Protocol default

ID	Device Name	IP Address	Port	Protocol
1	IPCAM	192.168.1.168	80	N1

2

Search

Match Code

3

Add One

Modify IP

Advanced

< 1 / 1 >

Channel	Device Name	IP Address	Status
▲ 1	IPCAM	172.20.14.31	Connect Success
2	IPCAM	172.20.14.244	Connect Success
3			No Video Source
▼ 4			No Video Source
5			No Video Source
6			No Video Source
7			No Video Source
8			No Video Source

Delete

Delete All

Manual Edit

Channel Setup

Wireless Setup

Repeater

1

Wireless Add

Searching and adding cameras, please wait ...

Channel 3 added successfully

Channel	IP Address	MAC Address
1	172.20.14.31	9c:a3:a9:24:42:a0
2	172.20.14.244	9c:a3:a9:3c:a8:bd
3	172.20.14.130	9c:a3:a9:38:f6:91
4		
5		
6		
7		
8		