

## How to turn off the floodlight at night?

The floodlight will automatically switch on at night when detect any suspicious activities and offer true color videos. But you can customize the IR-Cut mode to turn off the floodlight:

- ① Please double click the selected channel to enter full screen mode.
- ② Right click mouse to enter menu "Color Adjust", IRcut mode select "Infrared mode" and click "Ok" to save the setting.



IR Cut Mode	Floodlight Camera	
	Day	Night
Infrared	Color Picture	Black & White, floodlight will never turn on
Daylight	Color Picture	Totally black once ambient light is insufficient, floodlight will never turn on
Night	Black & White	Black & White, floodlight will never turn on
Full Color	Color picture	Color picture, floodlight always turns on at night
Smart	Color picture	Black & white when No one passby, and floodlight switch on to offer color video once someone pass by and human activated

### Note:

- A The light of floodlight camera lasts for about 20 seconds.
- B The time interval for floodlight is about 2 minutes.
- C Only under the "Full color" mode and "Smart" mode, the floodlight will turn on when human detect people in the monitoring area.